

## CMT-EP707

Micro System



### KEY FEATURES

- Unique Tray Loading 3-Disc CD Changer
- Front Speakers: 15 Watts Per Channel x 2 (4 ohms, 1 kHz, 10% THD)
- Full Logic Auto Reverse Cassette Deck
- Mega Bass®



### ADDITIONAL FEATURES

#### General Features

- Tuner with 20 FM + 10 AM Station Presets
- Full Logic Auto Reverse Cassette Deck

#### Audio Features

- Mega Bass®
- Preset Music EQ Settings: ROCK, POP, JAZZ, FLAT

#### Inputs and Outputs

- Headphone (Mini Pin Jack)
- Audio Input 1 (MD) (RCA Type)
- Optical Digital Output (Toslink Type)

#### Convenience Features

- Sleep/Daily/Record Timer
- Display Dimmer

# CMT-EP707

Micro System

## KEY TECHNOLOGY

**Radio Presets** Finding your favorite radio stations over and over again can be tiring. With Sony's radio preset system, the user has two ways to store their favorite music. The first way a user can access is by automatic tuning preset. This system allows for automatic tuning of all stations that can be received in your area. The second method of storing preset stations involves manual searching. Under the manual preset storing method, the user is able to manually tune and store the radio frequency of their favorite stations (this method works well when trying to program weaker station signals).

**Sleep Timer/Daily Timer** Fall asleep to your favorite CD, Tape, or Radio Station, or wake up to your favorite music. All of this flexibility can be yours with every Sony 2002 Micro System. The sleep timer can be set to turn off your music after 10-90 minutes of time. Daily Timer allows for the unit to turn on and play your favorite music at the exact time desired.

## ADDITIONAL FEATURES

### Specifications

#### Amplifier Section

- Front Speakers: 15W x 2 (4 ohms, 1 kHz, 10% THD)
- Input Sensitivity/Impedance: MD Audio Input: 450mV, 47 kohm
- Output Impedance: Phones (Stereo Mini Pin Jack): Accepts Headphones of 8 ohms or more  
Front Speaker: Accepts Impedance of 8 to 16 ohms.

#### CD Player Section

- Laser (Semiconductor Laser): 780nm CD
- Frequency Response: 2Hz-20kHz (±0.5 dB)
- Optical Digital Output: Supports 660nm

#### Tuner Section

- FM Stereo, FM/AM Superheterodyne Tuner
- FM Tuner Section: Tuning Range: 87.5-108.0MHz  
Antenna: FM Lead Antenna  
Antenna Terminals: 75 ohms Unbalanced
- AM Tuner Section: Tuning Range: 530-1,710kHz  
Antenna: AM Loop Antenna  
Antenna Terminals: External Antenna Terminal

#### Front Speaker

- Speaker System: 2 Way Bass Reflex Type
- Speaker Units: 4" Woofer, 1" Tweeter
- Nominal Impedance: 4 ohms

### General

- Power Requirements: AC120V, 60Hz  
38W, (0.5W Standby)

### Accessories

#### Supplied Accessories

- Instruction Manual
- Remote Commander® Remote Control RM-SEP707
- AM Loop Antenna
- FM Lead Antenna

### Weights & Measures

- Main Unit: Approx. Dimensions (W/H/D): 7" x 9.6" x 13.1"  
Approx. Weight: 11 lbs.
- Front Speaker: Approx. Dimensions (W/H/D): 6.6" x 9.6" x 7.2"  
Approx. Weight: 4.8 lbs.